


MOTOROLA

DESCRIPTION — The SN54LS/74LS47 are Low Power Schottky BCD to 7-Segment Decoder/Drivers consisting of NAND gates, input buffers and seven AND-OR-INVERT gates. They offer active LOW, high sink current outputs for driving indicators directly. Seven NAND gates and one driver are connected in pairs to make BCD data and its complement available to the seven decoding AND-OR-INVERT gates. The remaining NAND gate and three input buffers provide lamp test, blanking input/ripple-blanking output and ripple-blanking input.

The circuits accept 4-bit binary-coded-decimal (BCD) and, depending on the state of the auxiliary inputs, decodes this data to drive a 7-segment display indicator. The relative positive-logic output levels, as well as conditions required at the auxiliary inputs, are shown in the truth tables. Output configurations of the SN54LS/74LS47 are designed to withstand the relatively high voltages required for 7-segment indicators.

These outputs will withstand 15 V with a maximum reverse current of 250 μ A. Indicator segments requiring up to 24 mA of current may be driven directly from the SN74LS47 high performance output transistors. Display patterns for BCD input counts above nine are unique symbols to authenticate input conditions.


The SN54LS/74LS47 incorporates automatic leading and/or trailing-edge zero-blanking control (RBI and RBO). Lamp test (LT) may be performed at any time which the BI/RBO node is a HIGH level. This device also contains an overriding blanking input (BI) which can be used to control the lamp intensity or to inhibit the outputs.

- LAMP INTENSITY MODULATION CAPABILITY
- OPEN COLLECTOR OUTPUTS
- LAMP TEST PROVISION
- LEADING/TRAILING ZERO SUPPRESSION
- INPUT CLAMP DIODES LIMIT HIGH-SPEED TERMINATION EFFECTS

SN54LS47 SN74LS47


BCD TO 7-SEGMENT DECODER/DRIVER LOW POWER SCHOTTKY

LOGIC SYMBOL



V_{CC} = Pin 16
GND = Pin 8

CONNECTION DIAGRAM DIP (TOP VIEW)



J Suffix — Case 620-08 (Ceramic)
N Suffix — Case 648-05 (Plastic)

PIN NAMES

LOADING (Note a)

	HIGH	LOW
A, B, C, D	0.5 U.L.	0.25 U.L.
RBI	0.5 U.L.	0.25 U.L.
LT	0.5 U.L.	0.25 U.L.
BI/RBO	0.5 U.L.	0.75 U.L.
a, b, c, d, e, f, g	1.2 U.L.	2.0 U.L.
Outputs	Open-Collector	15 (7.5) U.L.



Notes:

a) 1 Unit Load (U.L.) = 40 μ A HIGH, 1.6 mA LOW

b) Output current measured at $V_{OUT} = 0.5$ V

Output LOW drive factor is 7.5 U.L. for Military (54) and 15 U.L. for Commercial (74)
Temperature Ranges.

LOGIC DIAGRAM



NUMERICAL DESIGNATIONS – RESULTANT DISPLAYS

TRUTH TABLE

	INPUTS						OUTPUTS								
DECIMAL OR FUNCTION	LT	RBI	D	C	B	A	B1/RBO	a	b	c	d	e	f	g	NOTE
0	H	H	L	L	L	L	H	L	L	L	L	L	L	H	A
1	H	X	L	L	L	H	H	H	L	L	H	H	H	H	A
2	H	X	L	L	H	L	H	L	L	H	L	L	H	L	
3	H	X	L	L	H	H	H	L	L	L	L	H	H	L	
4	H	X	L	H	L	L	H	H	L	L	H	H	L	L	
5	H	X	L	H	L	H	H	L	H	L	L	H	L	L	
6	H	X	L	H	H	L	H	H	H	L	L	L	L	L	
7	H	X	L	H	H	H	H	L	L	L	H	H	H	H	
8	H	X	H	L	L	L	H	L	L	L	L	L	L	L	
9	H	X	H	L	L	H	H	L	L	L	H	H	L	L	
10	H	X	H	L	H	L	H	H	H	L	L	L	H	L	
11	H	X	H	L	H	H	H	H	H	L	L	H	H	L	
12	H	X	H	H	L	L	H	H	L	H	H	H	L	L	
13	H	X	H	H	L	H	H	L	H	H	L	H	L	L	
14	H	X	H	H	H	L	H	H	H	L	L	L	L	L	
15	H	X	H	H	H	H	H	H	H	H	H	H	H	H	
B1	X	X	X	X	X	X	L	H	H	H	H	H	H	H	B
RBI	H	L	L	L	L	L	L	H	H	H	H	H	H	H	C
LT	L	X	X	X	X	X	H	L	L	L	L	L	L	L	D

H = HIGH Voltage Level

L = LOW Voltage Level

X = Immaterial

NOTES:

- B1/RBO is wire-AND logic serving as blanking input (B1) and/or ripple-blanking output (RBO). The blanking out (B1) must be open or held at a HIGH level when output functions 0 through 15 are desired, and ripple-blanking input (RBI) must be open or at a HIGH level if blanking of a decimal 0 is not desired. X = input may be HIGH or LOW.
- When a LOW level is applied to the blanking input (forced condition) all segment outputs go to a LOW level regardless of the state of any other input condition.
- When ripple-blanking input (RBI) and inputs A, B, C, and D are at LOW level, with the lamp test input at HIGH level, all segment outputs go to a HIGH level and the ripple-blanking output (RBO) goes to a LOW level (response condition).
- When the blanking input/ripple-blanking output (B1/RBO) is open or held at a HIGH level, and a LOW level is applied to lamp test input, all segment outputs go to a LOW level.